

## India PAL B Frequency Plan

---

The following table lists the India (PAL B) Frequency Plan (V/S Spacing + 5.5 MHz) on the two CHANNEL rotary switch on the front panel.

GI Channel Number	India Channel Number	Vision	Aural
IF		38.9	33.4
02	E2	48.25	53.75
03	E3	55.25	60.75
04	E4	62.25	67.75
71	X	69.25	74.75
72	Y	76.25	81.75
73	Z	83.25	88.75
74	Z+1	90.25	95.75
75	Z+2	97.25	102.75
05	S1	105.25	110.75
06	S2	112.25	117.75
07	S3	119.25	124.75
08	S4	126.25	131.75
09	S5	133.25	138.75
10	S6	140.25	145.75
11	S7	147.25	152.75
12	S8	154.25	159.75
13	S9	161.25	166.75
14	S10	168.25	173.75
15	E5	175.25	180.75
16	E6	182.25	187.75
17	E7	189.25	194.75
18	E8	196.25	201.75
19	E9	203.25	208.75
20	E10	210.25	215.75
21	E11	217.25	222.75
22	E12	224.25	229.75
23	S11	231.25	236.75
24	S12	238.25	243.75

GI Channel Number	India Channel Number	Vision	Aural
25	S13	245.25	250.75
26	S14	252.25	257.75
27	S15	259.25	264.75
28	S16	266.25	271.75
29	S17	273.25	278.75
30	S18	280.25	285.75
31	S19	287.25	292.75
32	S20	294.25	299.75
33	S21	303.25	308.75
34	S22	311.25	316.75
35	S23	319.25	324.75
36	S24	327.25	332.75
37	S25	335.25	340.75
38	S26	343.25	348.75
39	S27	351.25	356.75
40	S28	359.25	364.75
41	S29	367.25	372.75
42	S30	375.25	380.75
43	S31	383.25	388.75
44	S32	391.25	396.75
45	S33	399.25	404.75
46	S34	407.25	412.75
47	S35	415.25	420.75
48	S36	423.25	428.75
49	S37	431.25	436.75
50	S38	439.25	444.75
51	S39	447.25	452.75
52	S40	455.25	460.75
53	S41	463.25	468.75
54	21	471.25	476.75
55	22	479.25	484.75
56	23	487.25	492.75
57	24	495.25	500.75
58	25	503.25	508.75
59	26	511.25	516.75

---

<b>GI Channel Number</b>	<b>India Channel Number</b>	<b>Vision</b>	<b>Aural</b>
60	27	519.25	524.75
61	28	527.25	532.75
62	29	535.25	540.75
63	30	543.25	548.75
64	31	551.25	556.75
65	32	559.25	564.75
66	33	567.25	572.75
67	34	575.25	580.75
68	35	583.25	588.75
69	36	591.25	596.75
70	37	599.25	604.75

---